

Advantage through innovation - SeCa CC100 PREMIUM

Midi 100 PREMIUM radio siren and flasher

Function



This combined radio siren and flasher receives alarms from the CC100 PREMIUM radio fire alarm control panel or the 100 PREMIUM radio repeaters and provides an acoustic and/or visual signal. It includes lithium batteries. The siren stops its acoustic signal automatically after 30 minutes as long as no new alarm has been reported. After 4 minutes, the flasher changes to an 8-second interval (previously 2 seconds). The Midi 100 PREMIUM radio siren and flasher is reset by shutting the alarm off at the control panel. Radio transmission of status reports is handled according to EN 54-25 (can be set to 100 – 300 sec.). The Midi 100 PREMIUM radio siren and flasher's system parameters (e.g., horn settings, status reports) are set by radio signal from the control panel.

Item number: 4600008

System features

Unique to the SeCa CC100 PREMIUM are the ability to use model 100 cascable radio repeaters to quadruple the range, as well as special functions for project planning and commissioning. Using the automatic commissioning function, you can start a "search" and with the help of up to 6,000 signal strength measurements it determines all components' communication paths to the control panel. Successful commissioning gives you the security of a stable radio connection. In addition, the SeCa CC100 PREMIUM offers comprehensive service functions inspired by practical experience and the ideas of many installers. Among the most important: an integrated analyser, battery and signal strength testing, signal strength charts, commissioning and maintenance logs, event memory, and remote monitoring.

Areas of application

We recommend the SeCa CC100 PREMIUM for the following applications: Hotels and inns, retirement homes, youth hostels, military barracks, schools and preschools, offices and administrative buildings. The system can always be installed in compliance with the legal requirements for smoke detectors.

Technical data

Frequency:	Transmits via the ISM band
Broadcast technology:	bidirectional, synchronized synthesizer technology
Power supply:	2 type CR123A 3V lithium batteries with a min. nominal capacity of 1400 mAh. Use only original batteries (item No. 5100154) or high-quality, tested batteries.
Rated current:	type 48 µA at factory default
Power consumption, alarm:	type 350 mA
Battery life:	approx. 2 years (with radio parameters at factory default), not counting alarm activations. Variation from factory default settings and extreme environmental conditions can shorten battery life by up to 15 months.
Operating temperature:	-10°C to +55°C
Storage temperature:	-20°C to +60°C
Acoustic indicator:	101 dB (at 1 m distance), tone change from 2400 Hz to 2850 Hz
Optical display:	Xenon flasher, Flash energy 0.7 joule
Dimensions:	Height 121 mm, depth 93 mm, weight 350 g
Material / colour:	Plastic, white, red

SeCa reserve the right to make changes.